

# TECHNICAL DATASHEET

PDU 32 Sockets IEC C13  
With 3L Surge Protector + AV6 Meter  
Input Ceeform 32A



3L Surge Protector



Input : Ceeform 32A



Output : (32) IEC C13



Cable : 3G\*6.0mm<sup>2</sup>\*3m



Max. Power : 8000 Watt

| <b>Specification</b>       |   |
|----------------------------|---|
| Brand                      | YURRO   |
| Product Name               | Power Distribution Unit   |
| Part Number                | Y-B32-6-5   |
| <b>Physical</b>            |   |
| Case                       | Aluminium alloy coated Black  |
| Power Input                | Bottom singel input   |
| Bracket Install            | Vertical installation   |
| Product Size               | L x W x H = 1628 x 50 x 60mm  |
| Mounting Length            | 1589mm  |
| Mounting Style             | 2 ends Brakets  |
| Fittings                   | 4 pcs cross screw ( φ 6 x 16mm), 4pcs M6 float nut  |
| <b>Output</b>              |   |
| Socket Type                | IEC C13   |
| Socket Unit                | 32 x IEC 13   |
| Max. Ouput Current         | 15A   |
| <b>Input</b>               |   |
| Cable with Plug            | Ceeform 32A   |
| Cable Spesification        | 3G*6.0mm <sup>2</sup> *3M   |
| Rating Voltage             | 220 - 250VAC 50 - 60 Hz   |
| Rating Current             | 32A   |
| Max. Current               | 32A   |
| Max. Power                 | 8000 watt   |
| <b>Protection Function</b> |   |
| 3LSP                       | 3Lights Surge Protector   |
| <b>Control Function</b>    |   |
| AV6                        | <ul style="list-style-type: none"> <li>. Monitor input voltage</li> <li>. Monitor power factor</li> <li>. Monitor frequency</li> <li>. Monitor total load power</li> <li>. Monitor total load current</li> <li>. Monitor energy consumption</li> <li>. Button reset energy</li> </ul> |
| <b>Add-In</b>              |   |
| Interior Connection Wire   | Brass bar   |
| Interior Connection Style  | Soldering tin   |
| Fix the Cable              | PG Cable clamp  |
| Safety Authentication      | CE  |
| <b>Warranty</b>            |   |
| 2 ( two ) Years            | Repair or replace   |